



**BUREAU
VERITAS**

Certificate of compliance

Applicant: SMA Solar Technology AG
Sonnenallee 1
34266 Niestetal
Germany

Product: Photovoltaic (PV) inverter

Model: STP3.0-3AV-40
STP4.0-3AV-40
STP5.0-3AV-40
STP6.0-3AV-40
STP8.0-3AV-40
STP10.0-3AV-40

Use in accordance with regulations:

Automatic disconnection device with three-phase mains surveillance in accordance with EN50549-1:2019 for photovoltaic systems with a three-phase parallel coupling via an inverter in the public mains supply. The automatic disconnection device is an integral part of the aforementioned inverter.

Applied rules and standards:

EN 50549-1:2019

Requirements for parallel connection of installations with distribution networks - Part 1: Connection to an LV distribution network - Production of installations up to and including Type B

DIN V VDE V 0126-1-1:2006 (4.1 Functional safety)

Automatic disconnection device between a generator and the public low-voltage grid

At the time of issue of this certificate the safety concept of an aforementioned representative product corresponds to the valid safety specifications for the specified use in accordance with regulations.

Report number: 18TH0325-EN50549-1_0

Certification Program: NSOP-0032-DEU-ZE-V01

Certificate number: U19-0506

Date of issue: 2019-09-13

Certification body



Holger Schaffer

Certification body Bureau Veritas Consumer Products Services Germany GmbH accreditation to DIN EN ISO/IEC 17065

A partial representation of the certificate requires the written approval of Bureau Veritas Consumer Products Services Germany GmbH

BUREAU
VERITAS

Annex to the EN 50549-1 certificate of compliance No. U19-0506

Appendix

Extract from test report according to EN 50549-1

Nr. 18TH0325-EN50549-1_0

Type Approval and declaration of compliance with the requirements of EN 50549-1.

Manufacturer / applicant:	SMA Solar Technology AG Sonnenallee 1 34266 Niestetal Germany					
Micro-generator Type	Photovoltaic (PV) inverter					
Rated values	STP3.0-3AV-40	STP4.0-3AV-40	STP5.0-3AV-40	STP6.0-3AV-40	STP8.0-3AV-40	STP10.0-3AV-40
MPP DC voltage range [V]	125 - 800	125 - 800	125 - 800	125 - 800	260 - 800	260 - 800
Input DC voltage range [V]	125 - 850	125 - 850	125 - 850	125 - 850	175 - 1000	175 - 1000
Input DC current [A]	2 x 12	2 x 12	2 x 12	2 x 12	20 / 12 max	20 / 12 max
Output AC voltage [V]	380/400/415 (3P,N,PE)	380/400/415 (3P,N,PE)	380/400/415 (3P,N,PE)	380/400/415 (3P,N,PE)	380/400/415 (3P,N,PE)	380/400/415 (3P,N,PE)
Output AC current [A]	4,5	5,8	7,6	9,1	12,1	14,5
Output power [VA]	3000	4000	5000	6000	8000	10000
Firmware version	V3.00.01.R					
Measurement period:	2018-07-11 to 2019-08-23					

Description of the structure of the power generation unit:

The power generation unit is equipped with a PV and line-side EMC filter. The power generation unit has no galvanic isolation between DC input and AC output. Output switch-off is performed with single-fault tolerance based on two series-connected relays in each line and neutral. This enables a safe disconnection of the power generation unit from the network in case of an error.

Appendix

Extract from test report according to EN 50549-1

Nr. 18TH0325-EN50549-1_0

Setting of the interface protection:

Parameter	Min. disconnection time	Max. disconnection time	Min. operate value	Max. operate value	Standard set value
Over voltage (stage 1) ^a	0,1s	100s	1,0V _n	1,2V _n	0,2s/1,2V _n
Over voltage (stage 2)	0,1s	5s	1,0V _n	1,3V _n	0,1s/1,25V _n
Under voltage (stage 1)	0,1s	100s	0,2V _n	1,0V _n	10s/0,2V _n
Under voltage (stage 2)	0,1s	5s	0,2V _n	1,0V _n	3s/0,8V _n
Over frequency	0,1s	100s	1,0f _n	1,04f _n	0,1s/1,03f _n
Over frequency (stage 1)	0,1s	5s	1,0f _n	1,04f _n	0,1s/1,03f _n
Under frequency	0,1s	100s	0,94f _n	1,04f _n	0,1s/0,95f _n
Under frequency (stage 2)	0,1s	5s	0,94f _n	1,04f _n	0,1s/0,95f _n
Reconnection settings for voltage	0,85V _n min, 1,1V _n max Adjustement range Min: 0-1V _n , Max:1-2V _n				0,85V _n (195,5V) ≤ V ≤ 1,10V _n (253V)
Reconnection settings for frequency	49,5Hz min,50,2Hz max Adjustement range: Min: 44-60 Hz, Max: 50-66 Hz				49,5Hz ≤ f ≤ 50,2Hz
Reconnection time	60s Adjustement range: 0-6000s				≥ 60s
Active power gradient after reconnection	10% Adjustement range: 1-10000%				10%PE _{max} / per minute
Permanent DC-injection	0,5% of rated inverter output current				
Loss of mains according EN 62116 (LoM)	2s				

Note:

^a Over voltage – stage1: 10 min-mean-value corresponding to EN 50160.

The above stated generators are tested according to the requirements in the EN 50549-1:2019. Any modification that affects the tests must be named by the manufacturer/supplier of the product to ensure that the product meets all requirements of the EN 50549-1:2019.